Power Transformers Horizontal 4766 - 4770

FILTRAN

LOW VOLTAGE RECTIFIER Transformer
with horizontal channel frames.

- Primary voltage,115 Volts, 60 Hz.
- Primary and secondary leads 8-10" long.
- 2-hole horizontal mounting.
- 5 sizes are available, covering the range: 10 to 50 VA.
- **CSA** listed (LR 47366).

MECHANICAL







Dimensions, Inches

P/N	DIMENSIONS L	W	H	PIN SPACING A
4766	3.25	2.00	2.00	2.81
4767	3.25	2.25	2.00	2.81
4768	3.69	2.13	2.31	3.13
4769	4.00	2.25	2.63	3.56
4770	4.00	2.50	2.63	3.56

ELECTRICAL SPECIFICATION

Part No.	Secondary Voltages (A-A) F.L. Volts	N.L. Volts	Current Amps
4766-01	6.3	7.25	1.20
4766-02	6.3	7.14	2.00
4766-03	10.0	11.00	1.00
4766-04	14.0	16.00	1.00
4766-05	20.0	22.00	0.50
4766-06	28.0	32.00	0.50
4766-07	30.0	34.20	0.50
4766-08	36.0	39.40	0.30
4766-09	44.0	50.60	0.25
4766-10	50.0	57.00	0.30
4767-01	8.5	9.60	2.00
4767-02	36.0	40.00	0.50
4767-03	16.0	17.60	1.00
4768-01	6.3	6.90	4.00
4768-02	8.5	9.50	3.00
4768-03	10.0	10.80	2.00
4768-04	12.6	13.80	2.00
4768-05	20.0	22.00	1.00
4768-06	25.0	27.50	1.00
4768-07	28.0	30.80	1.00
4768-08	44.0	48.10	0.50
4768-09	50.0	55.00	0.50

Part No.	Secondary Voltages (A-A) F.L. Volts	N.L. Volts	Current Amps
4769-01	14.0	15.30	2.00
4769-02	18.0	19.60	1.50
4770-01	8.5	9.04	4.00
4770-02	10.0	10.50	3.00
4770-03	16.0	17.00	2.20
4770-04	16.0	17.40	3.00
4770-05	20.0	21.40	2.00
4770-06	25.0	26.80	1.50
4770-07	33.0	35.00	1.00
4770-08	36.0	39.50	1.00
4770-09	44.0	47.40	1.00
4770-10	50.0	54.50	1.00
4770-11	60.0	65.20	0.50
4770-12	80.0	85.50	0.50
4770-13	100.0	107.00	0.50
4770-14	120.0	129.50	0.30

ISSUE: C 4760.CHP 9507/12

FILTRAN LTD
An ISO 9001 Registered Company
229 Colonnade Road, Nepean, Ontario, Canada K2E 7K3
Tel: (613) 226-1626 Fax: (613) 226-7124 www.filtran.com